

Voltage Range - 400 to 16 00 V Forward Current - 50 Ampere

# **THREE-PHASE BRIDGE RECTIFIER**


#### **FEATURES**

- I<sub>o</sub> 50A
- $V_{RRM}$  400V~1600V
- Glass passivated chip
- High surge forward current capability

### **APPLICATIONS**

 General purpose 3 phase Bridge rectifier applications

#### **Outline Dimensions and Mark**



## LIMITING VALUES (ABSOLUTE MAXIMUM RATING)

Item	Symbol	Unit	Conditions	SKPBC50						
				04	06	08	10	12	14	16
Repetitive Peak Reverse Voltage	$V_{RRM}$	V		400	600	800	1000	1200	14001	600
Average Rectified Output Current	Io	A	60Hz sine wave, R-load, with heatsink Ta=55℃	50						
Surge(Non- repetitive)Forward Current	$I_{FSM}$	A	60H <sub>Z</sub> sine wave, 1 cycle, T <sub>j</sub> =25°C	500						
Current Squared Time	I <sup>2</sup> t	$A^2S$	1ms≤t<8.3ms Tj=25°C, Rating of per diode	1040						
Storage Temperature	T <sub>stg</sub>	°C		-40 ~+150						
Junction Temperature	Tj	°C		-40~+150						
Dielectric Strength	V <sub>dis</sub>	KV	Terminals to case,AC 1 minute	2.5						

# Electrical Characteristics (Ta=25°C Unless otherwise specified)

Item	Symbol	Unit	Test Condition	Max
Peak Forward Voltage	$V_{FM}$	V	I <sub>FM</sub> =17A, Pulse measurement, Rating of per diode	1.2
Peak Reverse Current	verse Current $I_{RRM}$ $\mu$ $A$ $V_{RM}=V_{RRM}$ , Pulse measurement, Rating of per diode		10	
Thermal Resistance	Resistance R θ J-C ℃/W Between junction and case with heatsink		0.9	

This PDF is a property of Master Instrument Corporation.


Email: sales@micindia.com Website: www.micindia.com





Voltage Range - 400 to 16 00 V Forward Current - 50 Ampere


# THREE-PHASE BRIDGE RECTIFIER

## **CHARACTERISTICS(TYPICAL)**









## Disclaimer

All product, product specifications and data are subject to change without notice to improve reliability, function or design or otherwise.

Email: sales@micindia.com Website: www.micindia.com