

# **PCEM Family ERU 51**

Power choke e-Mobility for DC/DC converter application

Series/Type:

Ordering code: B78338\*A004

Date: 2018-10-09

Version: 07

<sup>©</sup> TDK Electronics AG 2018. Reproduction, publication and dissemination of this publication, enclosures hereto and the information contained therein without TDK Electronics' prior express consent is prohibited.

B78338\*A004

### Power choke e-Mobility for DC/DC converter application

#### Construction

- MnZn ferrite core
- Helical Winding

#### **Features**

- Number of turns: 3
- Maximum limited component temperature 150°C
- RoHS compatible
- Qualified with reference to AEC-Q200

### **Application**

■ Output Choke for boardnet converters in hybrid or electrical vehicles

#### **Terminals**

■ Hole for M4 screw, bare copper

#### **Delivery mode**

■ Cardboard box with 16 chokes on two levels in a box

### Marking

■ Product brand, ordering code, date code / production identification code


#### **Assembly**

Additional clamp to be considered by customer


### Circuit diagram




### **Dimensional drawing**



Alle Maßangaben in mm ! All dimensions in mm !





Terkin or understrand as for parallelism see for parallelism see in gebauten Zustand mensions in assembled state mensions in assembled state menses am unteren Kern asured at the lower core to Den- und Untersein kein Uberstan for maniorism or man and hatten side on maniorism.


Tolerance ISO 8015. Size ISO 14405 ©. ISO 2768-c

2018-10-09

B78338\*A004

# Power choke e-Mobility for DC/DC converter application

# **Packaging**



### Technical data and measuring conditions

Specified @ 25°C if not mentioned otherwise, all values without tolerance are typical values

Rated Inductance L <sub>R</sub>	Measured at terminals [1, 2], measuring conditions 100 kHz, 1 V			
Inductance tolerance	± 10%			
Saturation current I <sub>sat</sub>	Current that will result in approx. 20% drop in inductance values.			
	Temperature response needs to be verified in specific applications. Test results on request.			
DC resistance R <sub>typ</sub>	Measured at terminals [1, 2]			
High voltage: N1 - core	500 V <sub>dc</sub> , 1 s			
Switching frequency	200 kHz			
Operating temperature range	- 40 °C + 150 °C			

# Characteristics and ordering codes


L <sub>R</sub>	I <sub>sat 25°C</sub>	I <sub>sat</sub>	I <sub>sat</sub> 125°C	R <sub>DC</sub> (typ)	R <sub>DC</sub> (max)	Approx. Weight	Project	Ordering code
μΗ	Α	А	Α	mΩ	mΩ	g	Number	-
1.4	300	270	250	0.25	0.30	225	T8414	B78338P2320A004
2.1	205	185	170	0.25	0.30	225	T6823	B78338P2168A004
2.6	160	150	140	0.25	0.30	225	T8380	B78338P2315A004

Other inductance values are available, only on request


L vs. DC bias current IDC

Typical values, values calculated for 3 turns from measurement with 20 turns


### B78338P2320A004 (T8414):



### B78338P2168A004 (T6823):



# B78338P2315A004 (T8380):



B78338\*A004

### Power choke e-Mobility for DC/DC converter application

### **Cautions and warnings**

- Additional information is contained in our data books, which are also available on the
  internet. Particular attention should be paid to the derating curves given there. The
  soldering conditions given there should also be observed. Temperatures quoted in relation
  to wave soldering refer to the pin, not to the housing.
- If the components are to be washed varnished, it is necessary to check whether any washing varnish agent that is used has a negative effect on the wire insulation, any plastics that are used, or on glued joints. In particular, it is possible for washing varnish agent residues to have a negative effect in the long-term on wire insulation. Washing processes may damage the product due to the possible static or cyclic mechanical loads (e.g. ultrasonic cleaning). They may cause cracks to develop on the product and its parts, which might lead to reduced reliability or lifetime.
- The following points must be observed if the components are potted in customer applications:
  - Many potted materials shrink as they harden. They therefore exert a pressure on the
    plastic housing or core. This pressure can have a deleterious effect on electrical
    properties and, in extreme cases, can damage the core or plastic housing
    mechanically;
  - It is necessary to check whether the potting material used attacks or destroys the wire insulation, plastics or glue;
  - The effect of the potting material can change the high frequency behaviour of the components.
- Ferrites are sensitive to direct impact. This can cause the core material to flake, or lead to breakage of the core.

Even for customer specific products, conclusive validation of the components in the circuit can only be carried out by the customer.

#### Display of ordering codes for TDK Electronics products

The ordering code for one and the same product can be represented differently in data sheets, data books, other publications, on the company website, or in order-related documents such as shipping notes, order confirmations and product labels. The varying representations of the ordering codes are due to different processes employed and do not affect the specifications of the respective products. Detailed information can be found on the Internet under www.tdk-electronics.tdk.com/orderingcodes.

#### **Important notes**

The following applies to all products named in this publication:

- 1. Some parts of this publication contain statements about the suitability of our products for certain areas of application. These statements are based on our knowledge of typical requirements that are often placed on our products in the areas of application concerned. We nevertheless expressly point out that such statements cannot be regarded as binding statements about the suitability of our products for a particular customer application. As a rule we are either unfamiliar with individual customer applications or less familiar with them than the customers themselves. For these reasons, it is always ultimately incumbent on the customer to check and decide whether a product with the properties described in the product specification is suitable for use in a particular customer application.
- 2. We also point out that in individual cases, a malfunction of electronic components or failure before the end of their usual service life cannot be completely ruled out in the current state of the art, even if they are operated as specified. In customer applications requiring a very high level of operational safety and especially in customer applications in which the malfunction or failure of an electronic component could endanger human life or health (e.g. in accident prevention or life-saving systems), it must therefore be ensured by means of suitable design of the customer application or other action taken by the customer (e.g. installation of protective circuitry or redundancy) that no injury or damage is sustained by third parties in the event of malfunction or failure of an electronic component.
- 3. The warnings, cautions and product-specific notes must be observed.
- 4. In order to satisfy certain technical requirements, some of the products described in this publication may contain substances subject to restrictions in certain jurisdictions (e.g. because they are classed as hazardous). Useful information on this will be found in our Material Data Sheets on the Internet (www.tdk-electronics.tdk.com/material). Should you have any more detailed questions, please contact our sales offices.
- 5. We constantly strive to improve our products. Consequently, the products described in this publication may change from time to time. The same is true of the corresponding product specifications. Please check therefore to what extent product descriptions and specifications contained in this publication are still applicable before or when you place an order.
  - We also **reserve the right to discontinue production and delivery of products**. Consequently, we cannot guarantee that all products named in this publication will always be available. The aforementioned does not apply in the case of individual agreements deviating from the foregoing for customer-specific products.
- 6. Unless otherwise agreed in individual contracts, all orders are subject to our General Terms and Conditions of Supply.
- 7. Our manufacturing sites serving the automotive business apply the IATF 16949 standard. The IATF certifications confirm our compliance with requirements regarding the quality management system in the automotive industry. Referring to customer requirements and customer specific requirements ("CSR") TDK always has and will continue to have the policy of respecting individual agreements. Even if IATF 16949 may appear to support the acceptance of unilateral requirements, we hereby like to emphasize that only requirements mutually agreed upon can and will be implemented in our Quality Management System. For clarification purposes we like to point out that obligations from IATF 16949 shall only become legally binding if individually agreed upon.



### Important notes

8. The trade names EPCOS, CeraCharge, CeraDiode, CeraLink, CeraPad, CeraPlas, CSMP, CTVS, DeltaCap, DigiSiMic, ExoCore, FilterCap, FormFit, LeaXield, MiniBlue, MiniCell, MKD, MKK, MotorCap, PCC, PhaseCap, PhaseCube, PhaseMod, PhiCap, PowerHap, PQSine, PQvar, SIFERRIT, SIFI, SIKOREL, SilverCap, SIMDAD, SiMic, SIMID, SineFormer, SIOV, ThermoFuse, WindCap are trademarks registered or pending in Europe and in other countries. Further information will be found on the Internet at www.tdk-electronics.tdk.com/trademarks.

Release 2018-10