



GLASS PASSIVATED JUNCTION RECTIFIER


VOLTAGE 50 to 1000 Volt CURRENT 1 Ampere


FEATURES

- Plastic package has Underwriters Laboratory
- Flammability Classification 94V-O utilizing Flame Retardant Epoxy Molding Compound.
- Acquire quality system certificate: TS16949
- AEC-Q101 qualified
- Lead free in compliance with EU RoHS 2011/65/EU directive

MECHANCALDATA

- Case: Molded plastic, JEDEC DO-41
- Terminals: Axial leads, solderable per MIL-STD-750, Method 2026
- Polarity: Color Band denotes cathode
- Weight: 0.012 ounce, 0.3 gram.





MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

Ratings at 25°C ambient temperature unless otherwise specified. Single phase, half wave, 60 Hz, resistive or inductive load.

PARAMETER	SYMBOL	PG4001-AU	PG4002-AU	PG4003-AU	PG4004-AU	PG4005-AU	PG4006-AU	PG4007-AU	UNITS
Maximum Recurrent Peak Reverse Voltage	V _{RRM}	50	100	200	400	600	800	1000	V
Maximum RMS Voltage	V _{RMS}	35	70	140	280	420	560	700	V
Maximum DC Blocking Voltage	V _{DC}	50	100	200	400	600	800	1000	V
Maximum Average Forward Current 0.375"(9.5mm) Lead Length	I _{F(AV)}	1				А			
Peak Forward Surge Current : 8.3ms single half sine-wave superimposed on rated load		30					А		
Maximum Forward Voltage at 1A	V _F				1.1				V
Maximum DC Reverse Current at Rated DC Blocking T_=25°C Voltage T_j=100°C	I _R				1 50				μА
Typical Junction Capacitance (Note 1)	C _J				15				pF
Typical Thermal Resistance	R _{eJA}				50				°C/W
Operating and Storage Temperature Range	T _J ,T _{STG}	-55 to +150			°C				

NOTES:

- 1. Measured at 1 MHz and applied reverse voltage of 4 VDC.
- * JEDEC Registered Value





RATING AND CHARACTERISTIC CURVES




Fig.1-FORWARD CURRENTDERATING CURVE




Fig.2-TYPICAL INSTANTANEOUS FORWARD CHARACTERISTICS




Fig.3-TYPICALREVERSECHARACTERISTIC




Fig.4-MAXIMUMNON - REPETITIVESURGE CURRENT




Fig.5-TYPICALJUNCTIONCAPACITANCE





Part No_packing code_Version

PG4001-AU_AY_000A1

PG4001-AU_AY_100A1

PG4001-AU_B0_000A1

PG4001-AU_B0_100A1

PG4001-AU_R2_000A1

PG4001-AU_R2_100A1

For example:



Packing Code XX					Version Code XXXXX			
Packing type	1 st Code	Packing size code	2 nd Code	HF or RoHS	1 st Code	2 nd ~5 th Code		
Tape and Ammunition Box (T/B)	Α	N/A	0	HF	0	serial number		
Tape and Reel (T/R)	R	7"	1	RoHS	1	serial number		
Bulk Packing (B/P)	В	13"	2					
Tube Packing (T/P)	Т	26mm	Х					
Tape and Reel (Right Oriented) (TRR)	S	52mm	Y					
Tape and Reel (Left Oriented) (TRL)	L	PANASERT T/B CATHODE UP (PBCU)	U					
FORMING	F	PANASERT T/B CATHODE DOWN (PBCD)	D					





Disclaimer

- Reproducing and modifying information of the document is prohibited without permission from Panjit International Inc..
- Panjit International Inc. reserves the rights to make changes of the content herein the document anytime without notification. Please refer to our website for the latest document.
- Panjit International Inc. disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially occurred.
- Panjit International Inc. does not assume any and all implied warranties, including warranties
 of fitness for particular purpose, non-infringement and merchantability.
- Applications shown on the herein document are examples of standard use and operation.
 Customers are responsible in comprehending the suitable use in particular applications.
 Panjit International Inc. makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.
- The products shown herein are not designed and authorized for equipments relating to human life and for any applications concerning life-saving or life-sustaining, such as medical instruments, aerospace machinery et cetera. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Panjit International Inc. for any damages resulting from such improper use or sale.
- Since Panjit uses lot number as the tracking base, please provide the lot number for tracking when complaining.