

Product Search Data Sheet

Note: This datasheet may be out of date

Please download the latest datasheet of BLM18BA050SN1# from the official website of Murata Manufacturing Co., Ltd.

https://www.murata.com/en-eu/products/productdetail?partno=BLM18BA050SN1%23

BLM18BA050SN1#


"#" indicates a package specification code.


In Production RoHS REACH

< List of part numbers with package codes > BLM18BA050SN1B BLM18BA050SN1D BLM18BA050SN1J




Appearance & Shape





: Electrode (in mm)



The chip ferrite beads BLM series is designed to work nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted. BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

BLM_B series can minimize attenuation of the signal waveform due to its sharp impedance characteristics. Various impedances are available to match signal frequency.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance.



| Other Usage | For general |
|-------------|-------------|
| | |

Packaging Information

| Packaging | Specifications | Minimum Order Quantity |
|-----------|------------------|---------------------------|
| В | Bulk(Bag) | 1000 |
| D | 180mm Paper Tape | 4000 |
| J | 330mm Paper Tape | 10000 |

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





Note: This datasheet may be out of date

Please download the latest datasheet of BLM18BA050SN1# from the official website of Murata Manufacturing

Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM18BA050SN1%23

BLM18BA050SN1#

"#" indicates a package specification code.



| Shape | SMD |
|---------------------------------|--------------|
| Size Code (in mm) | 1608 |
| Size Code (in inch) | 0603 |
| Length | 1.6mm |
| Length Tolerance | ±0.15mm |
| Width | 0.8mm |
| Width Tolerance | ±0.15mm |
| Thickness | 0.8mm |
| Thickness Tolerance | ±0.15mm |
| Impedance (at 100MHz) | 5Ω |
| Impedance (at 100MHz) Tolerance | ±25% |
| Rated Current (at 85°C) | 500mA |
| Rated Current (at 125°C) | 500mA |
| DC Resistance(max.) | 0.2Ω |
| Operating Temperature Range | -55℃ to 125℃ |
| Mass(typ.) | 0.005g |
| Number of Circuit | 1 |

2 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering

without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



Product Search Data Sheet


Note: This datasheet may be out of date.

Please download the latest datasheet of BLM18BA050SN1# from the official website of Murata Manufacturing Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM18BA050SN1%23

BLM18BA050SN1#

"#" indicates a package specification code.





(Resistance element becomes dominant at high frequencies.)

Impedance-Frequency Characteristics

Equivalent Circuit

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering

3 of 3