
466 Series 1206 Fast-Acting Fuse



Additional Information







Resources

Accessories

Samples

Agency Approvals

Agency	Agency File Number	Ampere Range			
7 1	E10480	0.125 A - 5 A			
⊕ .	29862	0.125 A - 5 A			
(€	J50518280	0.125 A - 2 A			
UK	NA	0.125 A - 2 A			
\triangle	NA	0.125 A - 5 A			

(€ ĽK △ ROHS Ø HF 🕦 ®

Description

The 466 Series Fast-Acting Surface Mount Fuse (SMF) is a small (1206 size) thin-film device designed for secondary protection of circuits used in space constrained applications such as hand-held portable electronic devices.

This series is 100% lead-free and meets the requirements of the RoHS directive. New Halogen-Free 466 Series fuses are available to order using the "HF" suffix. See Part Numbering section for additional information.

Features & Benefits

- Product is compatible with lead-free solders and higher temperature profiles
- Product is marked on top surface with code to allow amperage rating identification without testing
- Low profile for height sensitive
 CE Mark indicates suitability applications
- Flat top surface for pick-andplace operations
- Element-covering material is resistant to industry standard cleaning operations

- Lead-free, Halogen-free and RoHS compliant
- Recognized to UL/CSA/NMX 248-1 and UL/CSA/NMX 248-
- Conforms to EN 60127-1 and EN 60127-7
- for the European Market
- UKCA Mark indicates suitability for the UK Market

Applications

Secondary protection for space constrained applications:

- Cell phones
- Battery packs
- Digital cameras
- DVD players
- Hard disk drives

Electrical Characteristics for Series


% of Ampere Rating	Opening Time at 25°C
100%	4 hours, Minimum
200%	5 sec., Maximum
300%	0.2 sec., Maximum

Electrical Specifications by Item

Ampere	A	Max	l	Nominal Cold	Nominal	Nom	Nom Power		Ager	icy Appr	ovals	
Rating (A)	Amp Code	Voltage Rating (V)	Interrupting Rating	Resistance (Ohms)	Melting I ² t (A ² sec)	Voltage Drop (mV)	Dissipation (W)	Œ	UK	A	71 .	(f)
0.125	.125	125		3.925	0.00064	634.37	0.0793	X	X	X	X	X
0.200	.200	125	50A @ 125VAC/	1.100	0.00055	254.28	0.0509	X	X	X	X	X
0.250	.250	125	VDC	0.691	0.0022	207.01	0.0518	X	X	X	X	X
0.375	.375	125		0.351	0.0045	169.18	0.0634	X	X	X	X	Х
0.500	.500	63		0.248	0.0060	158.47	0.0792	X	X	X	X	X
0.750	.750	63		0.106	0.0276	98.65	0.0740	X	X	X	X	X
1.00	001.	63		0.075	0.0423	79.97	0.0800	X	X	X	X	X
1.25	1.25	63	50A @ 63VAC/VDC	0.057	0.0640	85.71	0.1071	X	X	X	X	Х
1.50	01.5	63		0.046	0.1103	82.97	0.1244	X	X	X	X	X
1.75	1.75	63		0.038	0.1835	80.73	0.1413	X	X	X	X	X
2.00	002.	63		0.030	0.2326	78.73	0.1575	X	X	X	X	X
2.50	02.5	32		0.023	0.3516	76.99	0.1925	-	-	X	X	Х
3.00	003.	32	50A @ 32VAC/VDC	0.019	0.5760	75.99	0.2280	-	-	X	X	X
4.00	004.	32		0.014	1.764	74.50	0.2980	-	-	X	X	Х
5.00	005.	32		0.011	2.500	73.75	0.3688	-	-	Х	X	X
1 Measured at 10% of rated current 25°C. 2 Measured at rated voltage												

466 Series 1206 Fast-Acting Fuse

Temperature Re-rating Curve




1. Re-rating depicted in this curve is in addition to the standard re-rating of 25% for continuous operation.

Example:For continuous operation at 70 degrees celsius, the fuse should be rerated as follows: $I = (0.75)(0.80)I_{RAT} = (0.60)I_{RAT}$


2. The temperature derating curve represents the nominal conditions. For questions about temperature derating curve, please consult Littelfuse technical support for assistance.


Average Time Current Curves



Soldering Parameters

Reflow Con	dition	Pb – free assembly		
	-Temperature Min (T _{s(min)})	150°C		
Pre Heat	- Temperature Max (T _{s(max)})	200°C		
	-Time (Min to Max) (t _s)	60 – 180 seconds		
Average Ratto peak)	mp-up Rate (Liquidus Temp (T _L)	5°C/second max. 5°C/second max.		
$T_{S(max)}$ to T_L -	Ramp-up Rate			
Reflow	- Temperature (T _L) (Liquidus)	217°C		
nellow	-Temperature (t _L)	60 – 150 seconds		
Peak Tempe	rature (T _P)	260+0/-5 °C 20 – 40 seconds		
Time withir	n 5°C of actual peak Temperature			
Ramp-down Rate Time 25°C to peak Temperature (T _p) Do not exceed		5°C/second max.		
		8 minutes max.		
		260°C		







466 Series 1206 Fast-Acting Fuse


Product Characteristics

Materials	Body: Advanced High Temperature Substrate Terminations: 100% Tin over Nickel over Copper Element Cover Coat: Conformal Coating				
Operating	– 55°C to 90°C.				
Temperature	Consult temperature re-rating curve chart.				
Thermal Shock	Withstands 5 cycles of –55°C to 125°C				
Humidity	MIL-STD-202, Method 103, Condition D				
Vibration	MIL-STD-202, Method 201				
Insulation Resistance (After Opening)	Greater than 10,000 ohms				
Resistance to Soldering Heat	MIL-STD-202, Method 210, Condition D				


Part Marking System

Amp Code	Marking Code
.125	В
.200	С
.250	D
.375	E
.500	F
.750	G
001.	Н
1.25	J
01.5	K
1.75	L
002.	N
02.5	0
003.	P
004.	S
005.	Т

Dimensions



Part Numbering System



Packaging

Packaging Option	Packaging Specification	Quantity	Quantity & Packaging Code
8mm Tape and Reel	EIA-481 Rev. D (IEC 60286, part 3)	5000	NR

Disclaimer Notice - Littelfuse products are not designed for, and shall not be used for, any purpose (including, without limitation, automotive, military, aerospace, medical, life-saving, life-saving, life-saving or nuclear facility applications, devices intended for surgical implant into the body, or any other application in which the failure or lack of desired operation of the product may result in personal injury, death, or property damage) other than those expressly set forth in applicable Littelfuse product documentation. Warranties granted by Littelfuse shall be deemed void for products used for any purpose not expressly set forth in applicable Littelfuse documentation. Utterfuse shall not be liable for any claims or damages arising out of products used in applications not expressly intended by Littelfuse as as set forth in applicable Littelfuse documentation. The sale and use of Littelfuse products is subject to Littelfuse Terms and Conditions of Sale, unless otherwise agreed by Littelfuse. Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at www.littelfuse.com/disclaimer-electronics.

