Note: This datasheet may be out of date

Please download the latest datasheet of DLP31SN551ML2# from the official website of Murata Manufacturing

https://www.murata.com/en-eu/products/productdetail?partno=DLP31SN551ML2%23

# DLP31SN551ML2#

"#" indicates a package specification code.








< List of part numbers with package codes > DLP31SN551ML2B DLP31SN551ML2L



### Appearance & Shape







## **Applications**

Other Usage

For general



### Packaging Information

Packaging	Specifications	Minimum Order Quantity
В	Bulk(Bag)	500
L	180mm Embossed Tape	3000



### **Features**

DLP31S series is chip common mode choke coil that realizes high impedance in a small size with ferrite material technology and film processing technology. DLP31S series has excellent performance at high frequency range. It is suitable for differential signal line application.

#### Features

- 1. Small size, low profile, SMD. 3.2x1.6x1.15mm (Tolerance: +-0.15mm)
- 2. High common mode impedance (550 ohm at 100MHz typ.) in small size
- 3. DLP31S suppresses high frequency noise that was unable to be suppressed with existing common mode choke coils. Suitable for differential signal lines like USB, because DLP31S does not provide distortion to high speed signal transmission due to its high coupling (coupling coefficient: 0.98 min.)

#### **Applications**

- 1. USB lines of PCs, peripheral equipment
- 2. LVDS lines of Note-PCs, LCDs
- 3. USB lines of digital AV equipment such as digital cameras

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated : 2018/08/23

Note: This datasheet may be out of date

 $\underline{ Please \ download \ the \ latest \ data sheet \ of \ DLP31SN551ML2\# \ from \ the \ official \ website \ of \ Murata \ Manufacturing} }$ 

Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=DLP31SN551ML2%23

# DLP31SN551ML2#

"#" indicates a package specification code.



Shape	SMD
Size Code (in mm)	3216
Size Code (in inch)	1206
Length	3.2mm
Length Tolerance	±0.15mm
Width	1.6mm
Width Tolerance	±0.15mm
Thickness	1.15mm
Thickness Tolerance	±0.15mm
Common Mode Impedance (at 100MHz)	550Ω
Common Mode Impedance (at 100MHz) Tolerance	±20%
Rated Current	100mA
Rated Voltage	16Vdc
Withstanding Voltage	40Vdc
DC Resistance(max.)	3.6Ω
DC Resistance	3.6Ω max.
Insulation Resistance(min.)	100ΜΩ

Operating Temperature Range	-40°C to 85°C	
Mass(typ.)	0.03g	
Number of Circuit	1	
Operating Temperature Range(Self- temperature rise is included)	No	

2 of 3

#### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2018/08/23

<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Note: This datasheet may be out of date


 $\underline{ \text{Please download the latest datasheet of DLP31SN551ML2\# from the official website of Murata Manufacturing} \\$ 


https://www.murata.com/en-eu/products/productdetail?partno=DLP31SN551ML2%23

# DLP31SN551ML2#

"#" indicates a package specification code.








Impedance-Frequency Characteristics

Impedance-Frequency Characteristics (Main Items)



**Equivalent Circuit** 

3 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2018/08/23